Spectrum Cartridge Quick-System

Spectrum Pure Cartridge

Spectrum UltraPure Cartridge

Dissolved salt in the inflow depletes the ion exchange resin in the ***Spectrum Cartridge***. The conductivity increases and the required limit values can then no longer be met.
If the display shows warnings of excessive conductivity, the appropriate resin should be changed. After changing the resin tank, the system must be flushed for at least 15 minutes.

Open the locking lever and then release the pressure. Place a receptacle under the ventilation hose.	**Pull the connector off the container.**	**Replace the container with a new one. Tear the protective film where it is perforated and remove the protective cap.**
Push the connection onto the container as far as possible.	**Close the locking lever.**	**Vent and rinse the tank! (See below)**

Venting

For venting, the device must be ready for operation and turned on!
To vent both ***Spectrum cartridges***, close all extraction and flushing valves and wait until the pressure is at least 1.5 bar as displayed on the pressure gauge.
Open the locking lever, then press the red venting button until no more air flows out. Close the locking lever again.
If there is still air in the resin container, the procedure should be repeated.

Open the locking lever, then press the red venting button until no more air flows out.	**Close the locking lever again. If there is still air in the resin container, the procedure should be repeated.**

Rinsing after replacing the *Spectrum Cartridge*:

After replacing the ***Spectrum Cartridge*** it is recommended to rinse the device.
To do this, open the "Rinse Valve" completely for 15 minutes.

After the rinsing process, the "Rinse Valve" must be closed again. The device is now ready for operation again.

Disposal

The used water of the ***Spectrum Cartridge*** can be emptied into a sink, for example.

Disposal according to national regulations.

Safety warnings

Material Safety Data Sheet is available on request.

Warning!
Content causes serious eye irritation.
Prevention
Wash thoroughly after handling.
Wear eye protection/face protection.
Safety measures
IF IN EYES: Rinse cautiously with water for several minutes. Remove contact lenses, if present and easy to do. Continue rinsing.
If eye irritation persists: Get medical advice/attention.